

LED Batten Installation Manual

- Suitable for use with mains voltage of 200-240Vac.
- Luminaire suitable for both surface mounting and suspended mounting.
- This product is only suitable for indoor use.
- Turn off or isolate the mains supply before and during the installation.
- Must be installed or connected by licenced electrician.



1 Disconnect mains power before installation.

2 Use a screwdriver to unlock the end cap and open the cover before installation

3 Hold the base against the ceiling.
Mark the drill hole location on the ceiling with pencil.

4 Remove the base. Drill the holes and place the expansion plugs in the holes.

5 Thread the power cable into the fitting base through the sheathed cable hole and fix the base onto the ceiling with screws.
Select suitable Colour Temperature by Dip Switch
5CCT: 2700K-3000K-4000K-5000K-6500K
Default Setting: 6500K

6 Secure the Neutral, Earth and Live input wires in the terminal block.

7 Close the PC cover and end cap, then screw the screws on the end cap.

8 Turn the power switch back on to verify that the fitting is working properly.